



## SPECIFICATION FPG 3800E2

| Model          |                             | FPG 3800E2                                | FPG 3800E2             |
|----------------|-----------------------------|---|------------------------|
| Generator      | Starting Watts              | 2800Watts/2.8KW = 3.5KVA @50Hz            |                        |
|                | Running Watts               | 2500Watts/2.5KW = 3.2KVA @50Hz            |                        |
|                | Rated AC Voltage            | 220,230,240V                              |                        |
|                | Phase                       | Single Phase                              |                        |
|                | Voltage regulator           | AVR                                       |                        |
|                | Power Factor                | 1 W-KW/0.8KW-KVA                          |                        |
|                | Alternator Type             | Brush                                     |                        |
| Engine         | Engine Model                | SFE200E                                   | SFE200E                |
|                | Engine Type                 | Single Cylinder, 4-Stroke OHV Air Cooled  |                        |
|                | Displacement                | 196сс                                     |                        |
|                | Maximum output              | 6.5HP                                     |                        |
|                | Ignition System             | Breakless Ignition Type, Flywheel Magneto |                        |
|                | Starting System             | Recoil/Electric                           | Recoil/Electric/Remote |
|                | Fuel                        | Unleaded Automotive Gasoline              |                        |
|                | Capacity Fuel Tank          | 15 Litres                                 |                        |
|                | Lubricating Oil<br>Capacity | 0.6 L                                     |                        |
|                | Carburetor Type             | Float                                     |                        |
|                | Air Cleaner                 | Polyurethane Type                         |                        |
|                | P.T.O. shaft rotation       | Counter Clockwise (Facing P.T.O.)         |                        |
| Dime-<br>nsion | LXWXH                       | 725 X 485 X 470 mm                        |                        |
|                | Dry Weight                  | 57.9 KG                                   | 57.9 KG                |

Contact us for more details: 08033053993, 08053317814 & 08023023081

- GENERATORS
- ELECTRONICS
- REFRIGERATORS
- SANITARY WARES
- AIR CONDITIONERS

**Blessed David Nigeria Limited** is home to portable petrol generators, 100% copper, and one thing we can assure you with our whole heart and soul is Quality, you get what you asked for and we still stand with our Products after purchase, Manual, Key Starter & with Remote Control are available.

Delivery is Free Nationwide and is Payment On Delivery though not in all states.

## **Pay On Delivery**

- **Lagos State:** Receive the Generator in 8 hours maximum, the generator comes with free oil and a funnel.
- **Ogun State:** Receive the Generator in 24 hours maximum, the generator comes with free oil and a funnel.
- **Abuja.:** Receive the Generator in 72 hours maximum, the generator comes with free oil and a funnel.
- **Port-Harcourt:** Receive the Generator in 72 hours maximum, the generator comes with free oil and a funnel.
- **Other States:** Other states can be considered based on the arrangement with the buyer.

## **To Place Your Order Contact Us**

Call: **07026645627, 08023023081, 08033053993 & 08053317814** 

WhatsApp Hotline: 08053317814

To See All the Generators, Visit Our Website

https://vepaar.store/blesseddavidng