



SPECIFICATION

INFINITE SERIES

Model		IN4000CEW	IN4000CEW
Generator	Starting Watts	2800Watts/2.8kw = 3.5KVA @50Hz	
	Running Watts	2500Watts/2.5kw = 3.2KVA @50Hz	
	Rated AC Voltage	220,230,240V	
	Phase	Single Phase	
	Voltage regulator	AVR	
	Power Factor	1 W-KW/0.8KW-KVA	
	Alternator Type	Brush	
Engine	Fuel Consumption	11Hrs Running	11Hrs Running
	Engine Type	Single Cylinder, 4-Stroke OHV Air Cooled	
	Displacement	208cc	
	Maximum output	7HP	
	Ignition System	Breakless Ignition Type, Flywheel Magneto	
	Starting System	Recoil/Electric	Recoil/Electric/Remote
	Fuel	Unleaded Automotive Gasoline	
	Capacity Fuel Tank	15 Litres	
	Lubricating Oil Capacity	0.6 L	
	Noise Level	68 dB @ 7 Meters	
	Air Cleaner	Polyurethane Type	
	P.T.O. shaft rotation	Counter Clockwise (Facing P.T.O.)	
Dimension	L X W X H	715 X 460 X 460 mm.	
	Dry Weight	55KG	55KG