



SPECIFICATION

SENCI® SC 17000

Model		SC17000E	SC17000R
Generator	Starting Kva	11.0KVA @50Hz	
	Running Kva	10.0KVA @50Hz	
	Rated AC Voltage	220,230,240V	
	Phase	Single Phase	
	Voltage regulator	AVR	
	Power Factor	1	
	Alternator Type	Brush	
Engine	Engine Model	AP192FD	AP192FD
	Engine Type	Single Cylinder, 4-Stroke OHV Air Cooled	
	Displacement	459cc	
	Maximum output	18HP	
	Ignition System	Breakless Ignition Type, Flywheel Magneto	
	Starting System	Recoil/Electric	Recoil/Electric/Remote
	Fuel	PMS (Petrol)	
	Capacity Fuel Tank	25 Litres	
	Lubricating Oil Capacity	1.1 L	
	Carburetor Type	Float	
	Air Cleaner	Polyurethane Type	
	P.T.O. shaft rotation	Counter Clockwise (Facing P.T.O.)	
Dimension	L X W X H	786 X 568 X 612 mm.	
	Dry Weight	105KG	105KG