



## SPECIFICATION

## AC MASTER

Model		AC 6000E2	AC 6000E2
Generator	Starting Watts	4500Watts/4.5KW = 5.6KVA @50Hz	
	Running Watts	3600Watts/3.6KW = 4.5KVA @50Hz	
	Rated AC Voltage	220,230,240V	
	Phase	Single Phase	
	Voltage regulator	AVR	
	Power Factor	1 W-KW/0.8KW-KVA	
	Alternator Type	Brush	
Engine	Engine Model	SFE225E	SFE225E
	Engine Type	Single Cylinder, 4-Stroke OHV Air Cooled	
	Displacement	223cc	
	Maximum output	7.5HP	
	Ignition System	Breakless Ignition Type, Flywheel Magneto	
	Starting System	Recoil/Electric	Recoil/Electric/Remote
	Fuel	PMS (Petrol)	
	Capacity Fuel Tank	15 Litres	
	Lubricating Oil Capacity	0.6 L	
	Carburetor Type	Float	
	Air Cleaner	Polyurethane Type	
	P.T.O. shaft rotation	Counter Clockwise (Facing P.T.O.)	
Dimension	L X W X H	653 X 470 X 435 mm.	
	Dry Weight	62 KG	62 KG